

31/2 Digital Voltage、Ampere Frequency Meter				
型号规格 Model	互感器变化 PT	量程 Range	分辨率 Resolution	输入电阻 Input impedance
DP3-AV2	Direct input	2V	1mV	5M Ω
DP3-AV20	Direct input	20V	10mV	5M Ω
DP3-AV200	Direct input	200V	100mV	5M Ω
DP3-AV600	Direct input	600V	1V	5M Ω
DP3-AV3K	3KV:100	3KV	1V	5M Ω
DP3-AV10K	10KV:100	10KV	1V	5M Ω

31/2 Digital Voltage、Ampere Frequency Meter				
型号规格 Model	互感器变化 PT	量程 Range	分辨率 Resolution	输入电阻 Input impedance
DP3-DV2	Direct input	2V	1mV	5M Ω
DP3-DV20	Direct input	20V	10mV	5M Ω
DP3-DV200	Direct input	200V	100mV	5M Ω
DP3-DV600	Direct input	600V	1V	5M Ω

31/2 Digital Voltage、Ampere Frequency Meter				
型号规格 Model	互感器变化 PT	量程 Range	分辨率 Resolution	内部阻抗 Internal Impedance
DP3-DA0.0002	Direct input	200uA	100nA	1K Ω
DP3-DA0.002	Direct input	2mA	1uA	100 Ω
DP3-DA0.02	Direct input	20mA	10uA	10 Ω
DP3-DA0.2	Direct input	200mA	100uA	1 Ω
DP3-DA2	Direct input	2A	1mA	0.1 Ω
DP3-DA20	20A:75mV	20A	10mA	5M Ω
DP3-DA100	100A:75mV	100A	100mA	5M Ω
DP3-DA200	200A:75mV	200A	100mA	5M Ω
DP3-DA1000	1000A:75mV	1000A	1A	5M Ω
DP3-DA2000	2000A:75mV	2000A	1A	5M Ω

(1) 表中所列配电流互感器、电压互感器、分流器其型号规格为基本型。其它量程如交流一次额定电流为 10A、15A、30A、75A、250A、1500A、..、直流一次额定电流为 10A、15A、30A、75A、1500A、...、交流一次额定电压为 1KV、6KV、11KV、35KV、110KV、...、均可按用户要求供货。

(2) 配交流电流互感器其二次额定电流为 5A，配交流电压互感其二次额定电压为 100V，配直流电流分流其二次额定电压为 75mV，若二次额定电流、电压为其它数值，用户需予以说明。

### Notes:

(1) The list of items CT and PT model is basic model. the other scale for example, the first AC is 10A、15A、30A、75A、250A、1500A、...、The first DC is 10A、15A、30A、75A、300A、1500A、...、the first AC voltage is 1KV、6KV、11KV、35KV、110KV、...、it according to customer's offers.

(2) With AC CT of the second ampere are 5A, AC PT of the second voltage is 100V, DC divider of the second voltage is 75mV. If the second ampere and voltage is other value, customer needs to remark.

31/2 Digital Voltage、Ampere Frequency Meter				
型号规格 Model	互感器变化 PT	量程 Range	分辨率 Resolution	内部阻抗 Input impedance
DP3-AA2	Direct input	2A	1mA	0.1 Ω
DP3-AA20	20A:5A	20A	10mA	5M Ω
DP3-AA100	100A:5A	100A	100mA	5M Ω
DP3-AA200	200A:5A	200A	100mA	5M Ω
DP3-AA1000	1000A:5A	1000A	1A	5M Ω
DP3-AA2000	2000A:5A	2000A	1A	5M Ω

### Technical Parameter

Max digit display	1999
Input type	Singla-end Input
A/D convert	Dual slope
Measuring speed	Abt. 2.5/sec
Overflow display	"1" or "1"
Polarity display	Only "--" display(only DC)
Accuracy	± 0.2%FS ± 3Digit
Power	AC110V/220V ± 10%, 50/60Hz
Power consumption	≤ 4.5VA
Withstand voltage	AC1500V 1min
Max Input	Voltage:1.2Xrated continous;
Insultation Resistance	DC 500V 20M Ω
Weight	adt. 400

### Terminal connections

